

*SBAH-821



*SBAL-600

SBAH-821 / SBAL-600

Features - SBAH-821

* 3 spaced outlets design provides room for the large transformer blocks
* 2-in-1 rocker switch integrated with a 15 Amp overload circuit breaker
* Sliding safety covers - help to protect users and their children, keep dust and debris away from unused outlets
* EMI / RFI noise filter - to eliminate AC line noise
* Surge protection - to provide a safety power to avoid damage from a surge strike
* Telephone line protection - protects your internet modem or FAX / TEL from surges and spikes
* Coax / DSS protection - protects the Antenna / CATV / MATV coaxial cable from surges and spikes
* Mounting key holes
* 6 feet SJT14AWG x 3C heavy duty power cord

Features - SBAL-600

* 2-in-1 rocker switch integrated with a 15 Amp overload circuit breaker
* Sliding safety covers—help to protect users and their children, keep dust and debris away from unused outlets
* Surge protection—to provide a safety power to avoid damage from surge strike
* Mounting key holes
* 4 feet SJT14AWG x 3C heavy duty power cord

Specifications

Model Name		SBAH-821	SBAL-600
Outlets Number		8	6
Outlets Type		American Type	
Electrical Rating		15A, 125VAC, 1875W	
Surge Energy Joule Rating		3240 J	241 J
Surge Protection Mode		L-N, L-G, N-G	L-N
Clamping Voltage		330 V	
Max. Peak Spike Current		216000A	12000A
Max. Spike Voltage		6kV	
EMI/RFI Noise Filter	Frequency	150 kHz~100 MHz	N/A
	Attenuation	Up to 60 dB	N/A
DSS/COAX Cable Protection	Jack Type	F Connector	N/A
	Breakdown Voltage	< 75 V	N/A
	Insertion Loss	< 0.1 dB	N/A
	Surge Arrestor	Gas Tube	N/A
TEL/FAX/MODEM Protection	Jack type	RJ11/6P2C (1 in 2 out)	N/A
	Energy	160J	N/A
Line Protection		1 Line	N/A
Surge Protected Indicator		Red	N/A
Ground OK Indicator		Green	N/A
Power OK Indicator		N/A	N/A
Surge Circuit Shut Down		Yes	N/A
Power Safety Shut Down (L-N)		Yes	N/A
Accessories		6 ft. TEL cord + 6 ft. Coax. Cable	N/A